

BRICON USING A SPLIT CABLE



TO RACE WITH TWO SPEEDY CLOCKS



- There are times when it would be a big bonus to be able to compete with two Speedy clocks.
- This may make it possible to overcome a number of hurdles such as where two clubs basket or read out at the same time, or where one race continues whilst another race needs to read out.
- Having two Speedy clocks will help overcome this problem and give you freedom and flexibility.

Required equipment

- A second Speedy clock (supplied with a wall holder and clock bag).
- A split cable (obtainable from Bricon UK).

Preparation Instructions

- (a) Ensure that the clocks are clearly labelled to identify one from the other and are not mixed up.
- (b) Ensure that your name and information for your pigeons is held on both clocks.
This is easy to carry out – you can either manually link each of the birds in your race team directly onto the second clock, or a quick and simple way is to have the information on your first clock transferred to the club computer and then transferred back to your second clock.
- (c) Disconnect the cable that goes into the wall holder where you previously put your first clock.
- (d) Connect the split cable on the end of that cable, which then gives two connectors ready for use.
- (e) Connect one of these connectors to the existing wall holder and one to the new wall holder.

On race day

- (f) Place either Speedy into a wall holder and let it start up – it will display 'clocking with xx ant' where xx is the number of antenna pads connected within your loft system.
- (g) After that checking this message is correct, place the second Speedy clock into the other wall holder – this clock will start up and display 'clocking in slave modus'.
- (h) You are now ready to time birds on any antenna pad that is connected to these two clocks.
 - (i) Speedy A will record birds that were basketed onto it as race birds, whilst birds that were not basketed using Speedy A will be recorded on it as trainers.
 - (j) Speedy B will record birds that were basketed onto it as race birds, whilst birds that were not basketed using Speedy B will be recorded on it as trainers.
- (k) Take great care to ensure that each Speedy clock is taken back to the same club that it was initially used for at race basketing.

USING A COMBINATION OF A SPEEDY AND A SPEEDY X-TREME

The Speedy clock should be connected first and allowed to start up before the Speedy X-treme clock is connected. The Speedy X-treme must be the clock showing as the slave.